

**AMENDMENTS TO THE CLAIMS**

Please amend the Claims as follows:

1. (currently amended) A modulated radio frequency carrier capable of transmitting a binary information stream made up of first and second binary states comprising:

a carrier frequency waveform made up of a continuous sequence of complete discrete wavelets;

said complete discrete wavelets being defined by a 360 degree cycle between crossover positions;

said crossover positions representing a substantially zero energy level; and,

said complete discrete wavelets having been modulated in accordance with said information stream by having altered the frequency of a single or non-zero positive integer number of said complete discrete wavelets that correspond to said first binary states of said information stream and not having altered the frequency of a single or non-zero positive integer number of said complete discrete wavelets that correspond to said second binary states of said information stream where the change of frequency from said carrier frequency waveform to said altered frequency wavelets starts at the zero degree phase angle and ends at the 360 degree phase angle resulting in a spectral output of multiple frequencies spread over a broad spectral band defined by the difference in frequency between said carrier frequency waveform and said altered frequency wavelets during said altered 360 degree cycle.

2. (previously amended) The modulated radio frequency carrier of claim 1 wherein:

any harmonics of said modulated radio frequency carrier that were generated when said complete discrete wavelets were altered have been reduced by filtering.

3. (currently amended) A method for transmitting binary information from a binary information stream over a radio frequency carrier comprising the steps of:

generating a radio frequency carrier at a select carrier frequency such that said radio frequency carrier has a waveform with a continuous sequence of complete discrete wavelets with similar amplitudes;

said complete discrete wavelets being defined by a 360 degree cycle between crossover positions of said radio frequency carrier waveform;

said crossover positions representing a substantially zero energy level;

receiving said information stream as a binary data sequence of first and second binary states;

modulating said radio frequency carrier in accordance with said binary data sequence by altering the frequency of a single or non-zero positive integer number of said complete discrete wavelets that correspond to said first binary states to derive first carrier binary signals and not altering the frequency of a single or non-zero positive integer number of said complete discrete wavelets that correspond to said second binary states of said information stream where the change of frequency from said carrier frequency waveform to said altered frequency wavelets starts at the zero degree phase angle and ends at the 360 degree phase angle resulting in a spectral output of multiple frequencies spread over a broad spectral band defined by the difference in frequency between said carrier frequency waveform and said altered frequency wavelets during said altered 360 degree cycle thereby generating an integer cycle modulated carrier made up of said first carrier binary signals and said second carrier binary signals; and,

broadcasting said integer cycle modulated carrier such that a integer cycle modulated radio frequency signal is generated.

4. (previously amended) The method of claim 3 wherein:

the modulating of said radio frequency carrier is carried out by altering the frequency of a single or non-zero positive integer number of said complete discrete wavelets while minimizing sideband distortions of said radio frequency carrier.

5. (original) The method of claim 3 wherein:

the generation of said radio frequency carrier is accomplished by a local oscillator having an oscillator output at a select carrier frequency.

6. (previously amended) The method of claim 3 comprising the additional step of:  
reducing of harmonics from said integer cycle modulated carrier by filtering said integer  
cycle modulated carrier.

7. (previously amended) The method of claim 3 wherein:  
broadcasting said integer cycle modulated carrier is accomplished using a Time Division  
Multiple Access system such that Time Division Multiple integer cycle modulated radio  
frequency signals are broadcasted.

8. (previously amended) The method of claim 3 wherein:  
broadcasting said integer cycle modulated carrier is accomplished using a Frequency  
Division Multiple Access system such that Frequency Division Multiple integer cycle modulated  
radio frequency signals are broadcasted.

9. (currently amended) A method for receiving radio frequency transmitted binary  
information that was derived from a binary information stream composed of a binary data  
sequence of first and second binary states that was modulated onto a radio frequency carrier  
which has a waveform with a continuous sequence of complete discrete wavelets with similar  
amplitudes defined by a 360 degree cycle between crossover positions representing a  
substantially zero energy level in which the radio frequency carrier has been modulated in  
accordance with said binary data sequence by altering the frequency of a single or non-zero  
positive integer number of said complete discrete wavelets that correspond to said first binary  
states to derive first carrier binary signals and not altering the frequency of a single or non-zero  
positive integer number of said complete discrete that correspond to said second binary states of  
said information stream where the change of frequency from said carrier frequency waveform to  
said altered frequency wavelets starts at the zero degree phase angle and ends at the 360 degree  
phase angle resulting in a spectral output of multiple frequencies spread over a broad spectral  
band defined by the difference in frequency between said carrier frequency waveform and said  
altered frequency wavelets during said altered 360 degree cycle thereby generating an integer  
cycle frequency modulated carrier made up of said first carrier binary signals and said second

carrier binary signals such that an integer cycle frequency modulated radio frequency signal was generated and broadcasted comprising the steps of:

receiving said integer cycle frequency modulated radio frequency signal through an antenna responsive to said carrier radio frequency signal;

extracting said integer cycle frequency modulated carrier from said integer cycle frequency modulated carrier radio frequency signal received by said antenna;

demodulating said integer cycle frequency modulated carrier by detecting the respective frequencies of a single or non-zero positive integer number of said complete discrete wavelets to identify said first binary states and said second binary states that correspond with said first carrier binary signals and said second carrier binary signals; and,

reconstructing said binary data sequence from said first binary states and said second binary states resulting in regeneration of said information stream.

10. (original) The method of claim 9 wherein:

broadcasting and receiving said integer cycle frequency modulated carrier is accomplished using a Time Division Multiple Access system such that Time Division Multiple integer cycle frequency modulated radio frequency signals are broadcasted and received.

11. (original) The method of claim 9 wherein:

broadcasting and receiving said integer cycle frequency modulated carrier is accomplished using a Frequency Division Multiple Access system such that Frequency Division Multiple integer cycle frequency modulated radio frequency signals are broadcasted and received.

12. (currently amended) A method for transmitting binary information from a binary information stream over a radio frequency carrier, receiving the radio frequency carrier, and converting the transmitted binary information back into an information stream comprising the steps of:

generating a radio frequency carrier at a select carrier frequency such that said radio frequency carrier has a waveform with a continuous sequence of complete discrete wavelets with similar amplitudes;

said complete discrete wavelets being defined by a 360 degree cycle between crossover positions of said radio frequency carrier waveform;

said crossover positions representing a substantially zero energy level;

receiving said information stream as a binary data sequence of first and second binary states;

modulating said radio frequency carrier in accordance with said binary data sequence by altering the frequency of a single or non-zero positive integer number of said complete discrete wavelets that correspond to said first binary states to derive first carrier binary signals and not altering the frequency of a single or non-zero positive integer number of said complete discrete wavelets that correspond to said second binary states of said information stream where the change of frequency from said carrier frequency waveform to said altered frequency wavelets starts at the zero degree phase angle and ends at the 360 degree phase angle resulting in a spectral output of multiple frequencies spread over a broad spectral band defined by the difference in frequency between said carrier frequency waveform and said altered frequency wavelets during said altered 360 degree cycle thereby generating an integer cycle frequency modulated carrier made up of said first carrier binary signals and said second carrier binary signals;

broadcasting said integer cycle frequency modulated carrier such that an integer cycle frequency modulated radio frequency signal is generated;

receiving said integer cycle frequency modulated radio frequency signal through an antenna responsive to said carrier radio frequency signal;

extracting said integer cycle frequency modulated carrier from said integer cycle frequency modulated carrier radio frequency signal received by said antenna;

demodulating said integer cycle frequency modulated carrier by detecting the respective frequencies of a single or non-zero positive integer number of said complete discrete wavelets to identify said first binary states and said second binary states that correspond with said first carrier binary signals and said second carrier binary signals; and,

reconstructing said binary data sequence from said first binary states and said second binary states resulting in regeneration of said information stream.

13. (previously amended) The method of claim 12 wherein:

the modulating of said radio frequency carrier is carried out by altering the frequency of said complete discrete wavelets while minimizing sideband distortions of said radio frequency carrier.

14. (original) The method of claim 12 wherein:

the generation of said radio frequency carrier is accomplished by a local oscillator having an oscillator output at a select carrier frequency.

15. (original) The method of claim 12 comprising the additional step of:

reducing of harmonics from said integer cycle frequency modulated carrier by filtering said integer cycle frequency modulated carrier.

16. (original) The method of claim 12 wherein:

broadcasting and receiving said integer cycle frequency modulated carrier is accomplished using a Time Division Multiple Access system such that Time Division Multiple integer cycle frequency modulated radio frequency signals are broadcasted and received.

17. (original) The method of claim 12 wherein:

broadcasting and receiving said integer cycle frequency modulated carrier is accomplished using a Frequency Division Multiple Access system such that Frequency Division Multiple integer cycle frequency modulated radio frequency signals are broadcasted and received.